



MA onPC fader wing

Art.No. 120125



With the MA onPC fader wing, MA Lighting meets the requests for a mobile control solution that supplies real faders and executors in connection with the free of charge grandMA2 onPC software. Furthermore the MA onPC fader wing offers 2,048 parameters in conjunction with the grandMA2 onPC software that can be sent via its four built-in DMX-ports as well as via Ethernet protocols.

To connect the MA onPC fader wing with the computer running the grandMA2 onPC software you just need a USB cable. Additionally, the MA onPC fader wing is designed to perfectly extend the MA onPC command wing and get the maximum out of the grandMA2 onPC software. To save USB connections the MA onPC fader wing daisy-chains the USB for the MA onPC command wing.

Whilst the MA onPC command wing is based on the command section of a grandMA2 console, the MA onPC fader wing resembles its fader section. In combination, the MA onPC fader wing and MA onPC command wing enable the look and feel of the grandMA2 onPC software to be as close to a real grandMA2 console as possible – and all this for a reasonable price! Furthermore the MA onPC fader wing offers clever details like a slot for a Kensington lock and a USB port to connect an external desk lamp. Thanks to these details and the ergonomic design working with the MA onPC fader wing on a daily basis becomes a breeze.

The MA onPC fader wing comes with the option to expand the parameter count up to 4,096 parameters. Therefore MA offers a wide range of possibilities for all applications. The MA 4Port Node onPC and MA 8Port Node onPC for example will add 2,048 parameters and four or eight DMX lines respectively.

Please regard that it is possible to connect one MA onPC command wing and up to two MA onPC fader wing together to a computer running grandMA2 onPC.



Features

- Real-time control for 2,048 parameters in combination with grandMA2 onPC (up to 65,536 parameters as backup in the MA system)
- Expandable up to 4,096 parameters
- 4 DMX out (XLR 5pin)
- Fader/executor section similar to grandMA2 layout
- 15 executor faders, 45 executor buttons, 15 button executors
- Individually backlit and dimmable silent (clickless) keys
- USB port for external desk lamp
- Integrated universal power supply)
- Light, handy & rock solid
- Ergonomic design
- Just connect via USB to any PC running grandMA2 onPC

Scope of delivery

Additional scope of delivery
 dust cover
 USB cable 1.9m
 power cord 1.9m IECC Plug (lockable) open end

Technical Specifications

Operating voltage/ Supply voltage	120V/230V, 50/60Hz (automatic detection)
Net weight	4.5kg / 9.9lbs
Power	40VA
Dimensions	365 x 395 x 70mm / 14.4 x 15.6 x 2.8inch
Output connectors	4 x XLR 5pin (DMX) 2 x USB
Input connectors	1 x USB

Article

Art.No.	Article
120125	MA onPC fader wing

Accessories

Art.No.	Article
121046	MA Case for MA onPC fader wing, black
120136	Dust cover MA onPC fader wing
121048	Case für MA onPC fader wing, passend für Tour Pack (by Major), schwarz



More product pictures

